

# **H&L Integration Procedure**





## **BEFORE YOU BEGIN**

Contact the H&L support team on 1800 778 340 to make sure they are available for the installation, as they may be required.

#### **Preparing the Terminal**

 Make sure the terminal is in Integrated mode. If it's already there, skip to #2. Menu → Terminal Settings → Operating mode → Integrated.



2. Menu  $\rightarrow$  Manage POS Pairing  $\rightarrow$  Blue + Don't push start yet - leave the terminal on this screen for now.





#### Pairing the Terminal with Spice

#### This process is in two parts.

- 1. Download and install the latest Spice from here: <u>https://spice.integration.mspenv.io/latest.exe</u>
- 2. Run the installer, and accept the EULA
- 3. Select Next Payments from the list of Payment providers
- 4. Enter the POS ID (This is usually the same as how the POS is identified. (E.g POS1, Lounge bar, Restaurant, Reception)
- 5. Enter the IP Address of the terminal from the screenshot above

#### **EFTPOS Terminal Pairing**

Payment provider	
Next Payments	~
POSID	
POS1	
EFTPOS address	
192.168.0.253	
Auto Addross Possilution	-
Auto Audress Resolution	
Pair	

- 6. Select **Start** on the Terminal, then Pair on **Spice**
- 7. Make sure the codes match, select Yes on the terminal. Then Finish

<ul> <li>▲ * № № 2:52p</li> <li>← pogo</li> </ul>	<b>EFTPOS Terminal Pairing</b>	Confirm Pairing Code
	Payment provider	Please confirm the following code is shown on the EFTPOS terminal:
· 🔗		ACF81D
Get ready to pair with POS	POS ID	
Info required	POS1	Cancel
Serial number 450-875-232	CEFTPOS address	
<b>Network</b> Wired Ethernet	192.168.0.253	
IP address 192.168.0.253		
	Auto Address Resolution	
START	Pair	



### Enabling H&L to use Pago

1. From the main screen, tap the **Downloads System Options** button in the top right-hand corner. *N.B This might also be called SETUP* 

STUBBY 6PK	STUBBY CTN	CAN 6PK	CAN CTN	CIDERS 750ml ICE	IMPORTED BEERS	RTD CTNS	Manag ment	ge CHI t FLOW	PS /ERS Calc	ulator F	Table unctions	Downloads System Options
Qty Descri	otion	Price /	A ExtPrice	# C								
					W/END DRAUGHT	JAMES SQUIRE	HA SU D	UHN PER RY	S/WARK BITTER	SWARK STOUT	TOOHEY'S EXTRA DRY	TOOHEY'S OLD
					XXXX FAMILY	BOAGS FAMILY	HAHN LIGHT	HAHN SUPER DRY 3.5 MID	HAHN ULTRA CRISP	FURPHY	IRON JACK BLACK	IRON JACK RED
					VB FAMILY	CASCADE PREM LIGHT	CROWN LAGER	MELBOURNE BITTER	ENTER QUANTITY	ENTER PLU	HOLD SALE	REFUND (-)
					CARLTON DRY		PU BLO	JRE INDE	CANCEL ITEM	CANCEL SALE	DELETE	REPRINT RECEIPT
					CARLTON DRAUGHT	CARLTON	GREAT NORTHERN ORIGINAL	GREAT NORTHERN SUPER CRISP	7	8	9	Fast EFTPO S
Check-in Cus	tomers		Total	(0) \$0.00	COOP	PER S SION	C00 P#	PERS	4	5	6	TENDER TYPES
					COOPERS STOUT	COOPERS DRY	COOPERS LAGER	COOPERS DARK	1	2	3	NO SALE
Transact	ion Live	Check-ins	5			COOPERS VINTAGE	COOPERS LIGHT	COOPERS MILD	SEARCH ITEM	0	•	FAST CASH

2. Click on System Options



3. Click Devices down next to System Options

Configuration Viewer	
Ontion	Value
	value
<sup>™</sup> Clerk	
🛎 Debtor	
🗈 Display	
🗉 Download	
■ EFTPOS	
■ General	
■ Group search	
🗉 Member	
Print / Receipts	
🗄 Reports	
Stock Transfers	
≝ Table	
Timers	
System Options Devices	Cancel Save & Close



 Expand EFTPOS from the list and change the EFTPOS Interface to Mx51 Spice Integration We recommend leaving the sub-options unchanged Click Update & Save

S Configuration Viewer		
Option	Value	
Barcode Scanner		
Card Reader		
Cash Drawers		2 2
Customer Display		
Display		2 2 E
□ EFTPOS		
EFTPOS Interface	MX51 Spice Integrate	2 2
Allow EETPOS coch out	<b>~</b>	
		2 2 2
	<b>*</b>	
EFT Receipt Printing	No Printing	
Interface handles printing	×	
Interface allows tipping	*	
Maximum Pre-Authorization	\$100.00	
Maximum amount cash out	\$200.00	
Use card name to identify tender	× · · · ·	
Interface handles surcharge	×	
Signature authorization for EFTPOS transaction	¥	E
Gift Card/eGiftcard		
System Options Devices 🙀 Update & Save		X Cancel Save & Close

5. You can confirm this has been done correctly in the previous window, which now has Setup MX51 Spice. There are no further steps required on that button, as its just port configuration for specific network requirements

Setup Exceed - Version 1.42	X			
System Options	Setup MX51 Spice			
Station Details	Bonus Offer			
Sysnet Database	Setup Surcharge			
Printers	Setup Cash Drawer			
Backup	Setup Store Card			
Compact & Repair	CHASE			
COM Ports	Charts Interface			
Exit				



6. When a transaction is processed, this window will come up Press **OK** to send the transaction to the terminal, or for a phone order, press MOTO



